



AX-MAZ28SWC-6V

INSTALLATION INSTRUCTIONS

AX-MAZ28SWC-6V Mazda (with center display screen) 2014-up*

*Visit AxxessInterfaces.com for up-to-date vehicle specific applications.

INTERFACE FEATURES

- Pre-wired ASWC-1 harness (ASWC-1 sold separately)
- Retains the factory backup camera
- Includes the AX-CAM6V 12-volt to 6-volt converter

INTERFACE COMPONENTS

- AX-MAZ28SWC-6V harness • AX-CAM6V 12-volt to 6-volt converter

APPLICATIONS

MAZDA		CX-5	2017-up	Mazda6	2016-up
CX-3	2016-up	Mazda3	2014-up	MX-5	2016-up

CAUTION! All accessories, switches, climate controls panels, and especially air bag indicator lights must be connected before cycling the ignition. Also, do not remove the factory radio with the key in the on position, or while the vehicle is running.

AXXESS Integrate • AxxessInterfaces.com

© COPYRIGHT 2017 METRA ELECTRONICS CORPORATION REV. 12/4/17



AX-MAZ28SWC-6V

INSTALLATION INSTRUCTIONS

Connections to be made

- Connect the **Black** wire to chassis ground, and also to the **Black** wire of the AX-CAM6V.
- Connect the **Red** wire labeled "Camera Power 6V" to the **Blue/Red** wire of the AX-CAM6V.
- Connect the **Red** wire labeled (ASWC-1 12v accessory) and the **Blue/White** wire from the AX-CAM6V to accessory power.

To the aftermarket radio:

- Connect the **Yellow** RCA jack to the backup camera input.

Installing the AX-MAZ28SWC-6V

With the key in the off position:

- After the radio has been tested and working, connect the AX-MAZ28SWC-6V harness to the vehicle, and then into the ASWC-1.
- Refer to the ASWC-1 instructions for radio connections and programming.

Note: Disregard the harness that comes with the ASWC-1.



KNOWLEDGE IS POWER
Enhance your installation and fabrication skills by enrolling in the most recognized and respected mobile electronics school in our industry.
Log onto www.installermatrix.com or call 800-354-4782 for more information and take steps toward a better tomorrow.



Metra recommends MECP certified technicians

AXXESS Integrate • AxxessInterfaces.com

© COPYRIGHT 2017 METRA ELECTRONICS CORPORATION REV. 12/4/17



AX-MAZ28SWC-6V

INSTRUCCIONES DE INSTALACIÓN

AX-MAZ28SWC-6V Mazda (con pantalla central) 2014 y mas*

* Visite AxxessInterfaces.com para aplicaciones específicas de vehículos actualizadas.

CARACTERÍSTICAS DE LA INTERFASE

- Arnés ASWC-1 precableado (el ASWC-1 se vende por separado)
- Retiene la cámara de reversa de fábrica
- Incluye el AX-CAM6V de 12 voltios al convertidor de 6 voltios

COMPONENTES DE LA INTERFASE

- Arnés AX-MAZ28SWC-6V • AX-CAM6V de 12 voltios al convertidor de 6 voltios

APLICACIONES

MAZDA					
CX-3	2016 y mas	CX-5	2017 y mas	Mazda6	2016 y mas
		Mazda3	2014 y mas	MX-5	2016 y mas

¡PRECAUCIÓN! Todos los accesorios, interruptores, paneles de controles de clima y especialmente las luces del indicador de las bolsas de aire deben estar conectados antes de ciclar la ignición. Además, no quite el radio de fábrica con la llave en la posición o de encendido ni con el vehículo funcionando.

AXXESS Integrate • AxxessInterfaces.com

© COPYRIGHT 2017 METRA ELECTRONICS CORPORATION REV. 12/4/17



AX-MAZ28SWC-6V

INSTRUCCIONES DE INSTALACIÓN

Conexiones que se deben hacer

- Conecte el cable **negro** a la tierra del chasis y también al alambre **negro** del AX-CAM6V.
- Conecte el cable **rojo** con la etiqueta "Camera Power 6V" al cable **azul/rojo** del AX-CAM6V.
- Conecte el cable **rojo** etiquetado (accesorio ASWC-1 12v) y el cable **azul/blanco** del AX-CAM6V a la corriente de accesorios.

Al radio de mercado secundario:

- Conecte el conector RCA **amarillo** a la entrada de la cámara de reversa.

Instalación del AX-MAZ28SWC-6V

Con la llave en la posición de apagado:

- Después de que se haya probado el radio y que esté funcionando, conecte el arnés AX-MAZ28SWC-6V al vehículo y luego al ASWC-1.
- Consulte las instrucciones de ASWC-1 para las conexiones del radio y la programación.

Nota: Ignore el arnés que viene con el ASWC-1.



EL CONOCIMIENTO ES PODER
Mejora sus habilidades de instalación y fabricación inscribiéndose en la escuela de dispositivos electrónicos móviles más reconocida y respetada de nuestra industria. Regístrese en www.installerinstitute.com o llame al 800-354-6782 para obtener más información y avance hacia un futuro mejor.



Metra recomienda técnicos con certificación del Programa de Certificación en Electrónica Móvil (Mobile Electronics Certification Program, MECP).

AXXESS Integrate • AxxessInterfaces.com

© COPYRIGHT 2017 METRA ELECTRONICS CORPORATION REV. 12/4/17